



Roman Blind System



To Pair the receiver and the remote

- ⇒ Using a paperclip or similar, press briefly the programming button in the bottom of the receiver unit to wake up the receiver.
- ⇒ Select the channel required on the remote (if applicable) and press the stop (middle) button
- ⇒ To add extra channels, repeat the process.

To set Limits

- ⇒ Using a paperclip or similar, press the programming button found on the back of the remote control until you hear a 'beep' to enter programming mode.
- ⇒ Move the blind to the bottom limit.
- ⇒ Press Stop.
- ⇒ Press Stop a second time to enter 'Micro-stepping' mode.
- ⇒ Press the right button for 2-3 seconds (until beeps) to store bottom limit.
- ⇒ Press the up button to send the blind moving towards the top.
- ⇒ Press Stop.
- ⇒ Press Stop a second time to enter 'Micro-stepping' mode.
- ⇒ Press the left button for 2-3 seconds (until beeps) to store top limit.
- ⇒ Limits are set.

Resetting

- ⇒ Using a paperclip or similar, press and hold the programming button in the bottom of the receiver unit until you hear two beeps, to wake up the receiver.
- ⇒ Then...
 - ⇒ To **delete** the stored **channels**—press and the **UP BUTTON**
 - ⇒ To **delete** the **limits**—press the **DOWN BUTTON**
 - ⇒ To **delete both limits and channels**—press the **STOP BUTTON**